

Mi·Light[®]

User Instruction

100W 5 IN 1 LED Controller

Model No.: PX1

Features

100W 5 in 1 (Single Color & CCT & RGB & RGBW & RGB+CCT) smart strip controller is our newly developed high-end LED controller controlled by wireless remote controller, also with smart phone control and 4G long distance control (need WiFi iBox or WiFi remote). The controller has auto-transmitting and auto-synchronizing function and with brightness, CCT, RGB, RGBW and RGB+CCT output mode. This controller adopt the widely used 2.4GHz wireless technology with the features of low power consumption, long signal transmitting and strong anti-interference, etc. One compatible remote control many controllers at the same time. Widely used on the controlling of hotel lighting and home lighting.

Parameters

Model No.: PX1

Input Voltage: AC180~240V 50/60Hz

Output Voltage: DC24V

PF: >0.5

Output Current (Max): 4.5A

Output Power (Max): 100W

Remote Control Distance: 30 m

ta: 50°C

tc: 85°C

Indicating lamp showing instruction


Indicating Lamp Color	Output Mode
White Light	Single Color Mode
Yellow Light	Dual White Mode
Red Light	RGB Mode
Green Light	RGBW Mode
Blue Light	RGB+CCT Mode

Self-protection for over current

When the output current is over 5A, automatic stop output, Indicating red light blinking.

Auto-synchronization function

Different controllers can work synchronously when they are started at different times, controlled by the same remote, under same dynamic mode and with same speed.




Remark:

1. Indicating Auto-transmitting.
2. Controller will be auto-synchronizing in the same dynamic modes and within 30m controlling distance.

Auto-transmitting Diagram


One strip controller can transmit the signals from the remote control to another controller within 30m, as long as there is a strip controller within 30m, the remote control distance can be limitless.



Remote Controller

Compatible with these remote controls (Purchased separately).

For more details, pls read the remote instruction.




Dynamic Mode Sheet


Saturation Adjustable both on static and dynamic mode.

Number	Dynamic mode		Brightness & Speed
	Brightness, Color Temperature	RGB / RGBW / RGB+CCT	
1	White gradual change	colors gradual change	Adjustable
2	White jump to change	White gradual change	
3	White Gradual + Jump to change	RGB color gradual change	
4	NC	7 colors jump to change	
5	NC	Random jump to change	
6	NC	RED Gradual + Jump to change	
7	NC	Green Gradual +Jump to change	
8	NC	Blue Gradual + Jump to change	
9	NC	White Gradual + Jump to change	




Controller connect to LED strip diagram



Controller connect to Single Color LED strip diagram



Controller connect to color temperature LED strip diagram



Attention

1. Please check whether the input voltage of the power supply is in accordance with the controller, and please check the connection of both the cathode and anode, otherwise the controller will be broken.
2. Please check whether the output voltage of the controller is in accordance with the LED strip, and please check the connection of both the cathode and anode, otherwise the controller will be broken.
3. Please don't connect wires with power on. Please turn on again only when it is in right connection and no short circuit.
4. Please do not use the controller in the place with widely range metal area or strong electromagnetic wave nearby, otherwise, the remote distance will be seriously affected .



Made in China